

## BATTERY CONTROLLER

# W-DIAL 9 VDC IP 68



Waterproof controller for 1, 2, 4 or 6 stations for battery-powered valve boxes. Backlit LCD display and large characters facilitate controller programming day or night. W-DIAL can work in both traditional stand-alone controller mode and in Fliwer mode connected by a link.

### PROGRAMMING

#### Timer mode

- 4 independent programs
- 3 starting times per program
- Running times: 1 - 240 minutes per station
- Watering schedule:
  - By 7-day calendar with individual day selection
  - By cycle with watering intervals of once every hour to once every 99 days
- Freeze program function (OFF)
- Manual start by customized durations on stations

#### Fliwer mode

- Infinite functionalities provided by Fliwer platform:
  - Guided by artificial intelligence
  - Remote-controlled by user

### TECHNICAL FEATURES

- Available in 1, 2, 4, 6 zone versions
- Wide backlit LCD display
- ABS body, fully waterproof (IP 68)
- Sensor connection
- Integrated radio connection to Fliwer system
- Powered by 4 X 1.5 Volt AA alkaline batteries
- Fast, waterproof connections for 9 VDC latching solenoids
- Maximum wire length to solenoids: 30 meters with 1.5 mm<sup>2</sup> wire size
- Provided with holder for valves boxes